

BASS OVERDRIVE BOD400

Authentic Tube-Sound Overdrive Effects Pedal

Thank you for showing your confidence in us by purchasing the BEHRINGER BASS OVERDRIVE BOD400. This high-quality effects pedal is specifically designed for bass applications. Thanks to its high-performance features you will achieve tube-like distortion, smooth sustain and super fat tone with maximum punch.

1. Controls



- 1 The **LEVEL** control adjusts the output level.
- 2 The **HIGH** control allows you to boost/cut the high-frequency range.
- 3 The **LOW** control allows you to boost/cut the low-frequency range.
- 4 Use the **GAIN** control to adjust the amount of overdrive.
- 5 With the **BAL(ance)** control you can adjust the amount of the dry direct signal and the effect signal.
- 6 The **ON/BATT** LED illuminates when the effect is activated. It also serves as a battery level indicator.
- 7 Use the footswitch to activate/deactivate the effect.
- 8 Use this 1/4" TS **IN** connector to plug in the instrument cable.
- 9 The 1/4" TS **OUT** connector sends the signal to your amp.

Use the **DC IN** connection at the front of the unit to plug in a 9 V power supply (not included).

The **BATTERY COMPARTMENT** is located underneath the pedal cover. To install or replace the 9 V battery, press the hinges with a ballpen and remove the pedal cover. Be careful not to scratch the unit.

- ♦ **The BOD400 has no on/off switch. As soon as you insert the jack into the in connector, the BOD400 begins running. When not using the BOD400, remove the jack from the in connector. This extends the life of the battery.**

The **SERIAL NUMBER** is located at the bottom.

2. Safety Instructions

Do not use near water, or install near heat sources. Use only authorized attachments/accessories. Do not service product yourself. Contact our qualified servicing personnel for servicing or repairs, especially when power supply cord or plug is damaged.

3. Warranty

Please register your new BEHRINGER equipment right after your purchase by visiting <http://behringer.com> and read the terms and conditions of our warranty carefully.

4. Specifications

In

Connector	¼" TS
Impedance	500 kΩ

Out

Connector	¼" TS
Impedance	1 kΩ

Power Supply

9 V $\overline{\text{=}}$, 100 mA regulated

BEHRINGER PSU-SB

USA/Canada	120 V~, 60 Hz
China/Korea	220 V~, 50 Hz
U.K./Australia	240 V~, 50 Hz
Europe	230 V~, 50 Hz
Japan	100 V~, 50 – 60 Hz
Power connector	2 mm DC jack, negative center
Battery	9 V type 6LR61
Power consumption	30 mA

Physical/Weight

Dimensions (H x W x D)	approx. 54 x 70 x 123 mm (2.1 x 2.8 x 4.8")
Weight	approx. 0.33 kg (0.7 lbs)

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may therefore differ from those listed or shown.

MUSIC Group accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph, or statement contained herein. Technical specifications, appearances and other information are subject to change without notice. All trademarks are the property of their respective owners. MIDAS, KLARK TEKNIK, LAB GRUPPEN, LAKE, TANNOY, TURBOSOUND, TC ELECTRONIC, TC HELICON, BEHRINGER and BUGERA are trademarks or registered trademarks of MUSIC Group IP Ltd. © MUSIC Group IP Ltd. 2017 All rights reserved.