



kramer

102MX

2-Channel Stereo Audio Mixer

| Microphone - 3.5/6.5mm



The 102MX is a high-performance 2-channel stereo audio mixer for line level and mic level audio signals. It mixes one line level input with either a microphone or a second line level input and produces a mixed audio output signal.

FEATURES

S/N Ratio - 69dB

Level (Gain) Control - Line 1 (or microphone), line 2, and master level

Selectable Microphone Input - Dynamic or condenser microphone with bias voltage

Talkover Button - Microphone input signal mutes line audio output when a microphone detects sound

Compact Kramer TOOLS™ - 3 units can be rack mounted side-by-side in a 1U rack space with the recommended rack adapter



kramer

TECHNICAL SPECIFICATIONS

| | |
|-----------------------|---|
| INPUTS: | Mic/line 1: 10mV/1.6k Ω , 1Vpp/10k Ω , on a 6.5mm phone connector; Line 2: 1Vpp/10k Ω , stereo on RCA connectors |
| OUTPUTS: | Line level, stereo, up to 5.6Vpp/150 Ω on RCA connectors |
| BANDWIDTH (-3dB): | 100kHz |
| GAIN RANGE: | -12dB to 68.5dB (mic); -12dB to +8.8dB (line) |
| DIFF. PHASE: | 0.05Deg |
| S/N RATIO: | 69dB |
| CONTROL: | Mic/line 1 level, line 2 level, master level rotary controls, condenser/dynamic mic, line/mic, talkover selection switches |
| AUDIO THD+NOISE: | 0.018% |
| 2nd HARMONIC: | 0.002% |
| POWER CONSUMPTION: | 12V DC, 40mA |
| INCLUDED ACCESSORIES: | Power supply, mounting bracket |
| Product Dimensions | 12.00cm x 7.15cm x 2.44cm (4.72" x 2.81" x 0.96") W, D, H |
| Product Weight | 0.2kg (0.4lbs) approx |
| Shipping Dimensions | 23.20cm x 12.00cm x 8.90cm (9.13" x 4.72" x 3.50") W, D, H |
| Shipping Weight | 0.5kg (1.1lbs) approx |

